

**Maximum** number of LED fittings on MCB's :

| MCB type      | type 1 | type 2 | type3 | type 4 | type D1 | type D2 | type D3 | type D4 |
|---------------|--------|--------|-------|--------|---------|---------|---------|---------|
| MCB10A type B | 31     | 20     | 13    | 8      | 13      | 15      | 11      | 18      |
| MCB13A type B | 40     | 26     | 17    | 10     | 17      | 19      | 14      | 23      |
| MCB16A type B | 50     | 33     | 21    | 13     | 21      | 24      | 18      | 29      |
| MCB20A type B | 62     | 41     | 26    | 16     | 26      | 30      | 22      | 36      |
| MCB25A type B | 78     | 51     | 32    | 20     | 32      | 37      | 28      | 45      |
| MCB10A type C | 31     | 34     | 21    | 13     | 21      | 24      | 18      | 29      |
| MCB13A type C | 40     | 44     | 28    | 17     | 28      | 32      | 24      | 39      |
| MCB16A type C | 100    | 56     | 35    | 22     | 35      | 40      | 30      | 49      |
| MCB20A type C | 62     | 68     | 43    | 27     | 43      | 49      | 37      | 60      |
| MCB25A type C | 78     | 85     | 54    | 33     | 54      | 62      | 46      | 75      |

Type 1 : fittings 1R : ECO 2ft

Type 2 : fittings 1R :9w, 13w, 17w,20w, 25w, 31w, , 35w, 44w + 3R : 17w, 23w, 30w, 45w, 56w, 66w

Type 3 : fittings 1R : 53w, 60w, ECO 4ft+5ft + 3R : 37w

Type 4 : fittings 76w up to 104w

Type D1 : DALI fittings 9w up to 60w + Casambi integrated in driver

Type D2 : DALI fitting 66w + MC-Connect

Type D3 : DALI fittings 76w up to 104w + **all Fridge versions**

Type D4 : DALI fittings Ecoline

**For multi-phase MCB's please reduce the number of fittings by 20%**

MCB = Miniature Circuit Breakers